

# MAGNETIC DOOR SENSE SWITCH

## SPEC SHEET



The **Magnetic Door Sense Switch** is a heavy-duty surface mounted magnetic door sense switch. Install on doors either alone or side by side in series and connect to any available I/O port on Audio Enhancement® network devices for seamless SAFE and EPIC System integration. An integral 6-foot stainless steel armored cable is included with each switch.



Switch



Magnet



Bracket

## SPECIFICATIONS

AC-2152 DOOR SENSE SWITCH	
Contents	(1) Door Sense Switch With 6 ft. Stainless Steel Armored Cable, (1) Door Mounted Magnet, (1) Adjustable Bracket, (4) Bolts, (4) Screws, (4) Nuts, (4) Washers, (1) Crimp Connection, (1) 2-gang Electrical Box With Cover, (2) Cable Clamps
Loop Type	Closed
Electrical Configuration	N/O (Normally Open)
Reed Form	A
Max. Initial Contact Resistance	.15 Ohms
Max. Contact Rating	10W
Max. Switching Voltage	200V DC
Max. Switching Current	.50 A
Weight	